



333 Bayview Avenue
Amityville, New York 11701
For Sales and Repairs, (800) 645-9445
For Technical Service, (800) 645-9440

© NAPCO 2004

RBAT-H1

DUAL BATTERY HARNESS

INSTALLATION INSTRUCTIONS

WI346 2/04

The RBAT-H1 Dual Battery Harness permits the parallel connection of a second rechargeable battery within an alarm control center enclosure.

INSTALLATION

NOTE: Failure to connect the RBAT-H1 in accordance with these instructions may result in damage to the cable, board, and/or batteries.

1. Remove connections to the existing battery and prepare space in the enclosure for the second battery.
2. First connect the BLUE ends of the RBAT-H1 to the battery leads coming from the circuit

board:

- RED wires to the RED lead
- BLACK wires to the BLACK lead

3. Install the second battery along side the first.
4. Connect either pair of RED ends to the first battery:
 - RED wire to the POSITIVE (+) terminal
 - BLACK wire to the NEGATIVE (-) terminal.
5. Similarly, connect the other pair of RED ends to the second battery:
 - RED wire to the POSITIVE (+) terminal
 - BLACK wire to the NEGATIVE (-) terminal

