


OmniTouch 7 Firmware Update




Updating OmniTouch 7 Firmware using PC Access Software

To obtain the latest firmware update for the OmniTouch 7, please follow these steps:

1. Start the PC Access Application.
2. From the “Help” menu, click “Check for Updates” to start the Updates Wizard.




3. Click “Next”.




4. If a PC Access update is available, download and install by clicking “Download”.

Note:


To obtain firmware updates for the OmniTouch 7, PC Access Version 3.12.0.716 or later must be installed.



- Next, the Updates Wizard will prompt you if controller firmware updates are available.
- Click “Next”.




7. Finally, the Update Wizard will prompt you if an OmniTouch 7 firmware update is available.
8. If OmniTouch 7 firmware update is available, click “Download” to download the update.




To update the OmniTouch 7 Firmware, please follow these steps:

1. Start the PC Access application.
2. Open the controller account file for the respective controller.
3. Click the “OmniTouch 7 Screens” menu item under “Extended Setup”.



4. Click the green plus icon to add a new OmniTouch 7 touchscreen.




5. On the OmniTouch 7 touchscreen, enter the Controller Address, Port, and Encryption Keys of the controller that you will be connecting to.
6. Select the language of the touchscreen from the “Language” drop-down menu.
7. Take note of the “Touchscreen IP” on the OmniTouch7 touchscreen, and then press “SAVE & EXIT”

The screenshot displays the configuration screen for the OmniTouch 7 Ver: 1.02. The interface is dark-themed with white text and input fields. The fields are as follows:


- Controller Address:** 10.0.0.41
- Controller Port:** 4369
- Encryption Keys:** Two fields containing the key 77-77-77-77-77-77-77-77. The second field is highlighted with an orange border.
- Touchscreen IP:** 10.0.0.144

Below the input fields is a numeric keypad with buttons for digits 0-9, letters A-F, and a back arrow with an 'X'. To the right of the keypad are three buttons: CLEAR, EXIT, and SAVE & EXIT.


8. Select “Network” from the “Options” menu.




9. Press the “Show Keys” button (the default password is “password”).




10. Enter the same IP Address, Port, and Encryption Keys that you entered on the OmniTouch 7.
11. Click "OK".




12. Press the “Update” button.




13. Navigate to the downloaded OmniTouch 7 firmware file, select it, and click “Open”.



14. Click “Next”.



15. The update process should begin. Wait until it completes.



16. Once it has completed, press “Close”.

The OmniTouch 7 touchscreen should restart.

